

# VT-E Series

4, 8, and 16 Channel Digital Video Recorders



## FEATURES

- 4, 8, or 16 Video Inputs
- Remote Viewing over the Internet or LAN
- Supports both Dynamic and Static IP Addresses
- Up to 120 IPS Recording
- MPEG-4 Compression
- 4 Audio Inputs / 1 Audio Output
- 4, 8, or 16 Channel Alarm Inputs
- Control locally via Front Panel, USB Mouse or with the Included IR Remote Control
- PTZ Control over RS-485
- Built-In Bandwidth Throttling



(888) VITEK-70 | [WWW.VITEKCCTV.COM](http://WWW.VITEKCCTV.COM)  
28492 Constellation Road Valencia, CA 91355

CYAN

MAGENTA

YELLOW

BLACK

# VT-E Series

4, 8, and 16 Channel Digital Video Recorders

Detailed Specifications	VT-E4	VT-E8	VT-E16
Video Standard	NTSC & PAL		
Video Inputs	4	8	16
Looping Outputs	4	N/A	N/A
Monitor Output	Composite / S-VHS 704 x 480 / 704 x 576		
Main Monitor Output	VGA		
Spot Output (Analog)	1	2	4
Split Screen	1 / 4	1 / 4 / 5 / 6 / 9	1 / 4 / 5 / 6 / 8 / 9 / 16
Audio	4 In / 1 Out		
Alarm	4 In / 1 Out (1 Relay)	8 In / 8 Out (TTL)	16 In / 16 Out (TTL)
Recording Speed	CIF (360 X 240), Half-D1 (720 X 240), D1 (720 X 480)		
Compression	MPEG-4 (Modified)		
Average File Size	CIF: 2~4k / Half D1: 4~6k / D1: 8~12k		
Internal Storage	2 x HDD (Max)		
Backup Options	External USB Devices (Flash Memory, HDD, CD/DVD+/-R, Etc.)		
Backup File Format	AVI		
Ethernet	RJ45 @ 10/100Mbps		
Bandwidth Throttling	8 Levels		
Dynamic IP support	Yes		
PTZ Control	RS-485		
USB	USB 2.0		
Pre / Post Event Buffer	Up to: 5 Seconds Pre-Event / 5 Minutes Post-Event		
Motion Area Setup	Adjustable 12 x 12 Grid	Adjustable 16 x 16 Grid	Adjustable 16 x 16 Grid
Operation Device	Front Panel / IR Remote Control / USB Mouse (Mouse Not Included)		
IR Remote Control	Included		
Power	100~240VAC, 1.0/1.5A, 60/50Hz		
Operation Temp.	32° ~ 113° Fahrenheit		
Humidity	0% ~ 80%		
Dimensions (W x H x D)	14.2" x 15.5" x 2.5"		
Weight	7.2lbs. (w/o HDD)		



(888) VITEK-70 | [WWW.VITEKCCTV.COM](http://WWW.VITEKCCTV.COM)  
28492 Constellation Road Valencia, CA 91355

CYAN

MAGENTA

YELLOW

BLACK